

# SUNDRAY AP S150 Wireless Access Point

## Product Overview

The S150 is an 802.11n wireless access point independently developed by Sundray. The S150 external 5dBi omnidirectional antenna supports 802.11b/g/n protocols with a maximum wireless access rate of 300Mbps, providing faster wireless Internet access and greater wireless coverage.

Sundray S150 provides 3 wired Ethernet ports, which can be wired to expand, such as access desktops, printers and so on.

The S150 supports DC local power supply and cooperates with the NAC series controllers to provide users with unprecedented rapid experience and more secure service access.

This series of products adopts a sleek design with an elegant appearance and convenient installation. It is suitable for desktop placement.



SUNDRAY AP S150

## Product Features

### Top-speed wireless network access

#### ➤ 11n high speed access

SUNDRAY AP-S150 series products comply with the 802.11b/g/n standard and adopt 2x2 MIMO technology, the highest transmission rate can reach 300 Mbps, providing high-performance wireless access services in terms of coverage scope, access density and operation stability.

#### ➤ GE uplink

A 10/100/1000Base-T Ethernet port is used as the uplink port and a GE port is used for uplink, breaking the restriction of traditional 100M transmission rate. The wired port is no longer the bottleneck of the wireless access rate.

➤ **QoS guarantee**

SUNDRAY AP-S150 supports different QoS levels. It supports air interface resource management based on applications, SSIDs or STAs to ensure that air interfaces are appropriately allocated and that the data of important SSIDs and applications is transmitted in preference. Transmission priorities can be defined for different service data through 802.11e/WMM. This ensures differentiated QoS levels.

➤ **L2 and L3 Seamless roaming**

SUNDRAY AP-S150 works with SUNDRAY wireless controller to implement seamless roaming for L2 and L3. When a wireless user roams, the IP address and authentication status remain unchanged. The terminal viscosity prevention function is provided to intelligently guide an STA to the optimal AP, increasing the roaming speed.

➤ **Terminal dragging prevention to ensure high-speed network access for all users on the entire network**

Terminal dragging prevention involves enabling terminals with different negotiated rates to occupy the identical wireless channel time by using the time fairness algorithm. This avoids problems of low wireless access speed, high delay and low network performance caused by low access rates of some terminals.

➤ **Intelligent load balancing**

In the case of high-density wireless users, SUNDRAY AP-S150 works with SUNDRAY wireless controller to implement intelligent load balancing based on the user quantity, traffic, and frequency band for the purpose of improving the bandwidth usage, thereby ensuring high wireless access speed for users.

**Intelligent RF to reduce wireless interference in an all-round way**

The work channel and transmit power of the wireless access point are adjusted automatically and interference from the surrounding environment is detected in real time to reduce radio interference in an all-round way and to improve the overall service quality of the wireless network.

**All-round security protection**

➤ **Multiple easy-to-use and secure authentication modes**

Multiple flexible, easy-to-use and secure user authentication modes are available. 802.1x, portal, SMS, WeChat, and QR code authentication modes are provided with the support of SUNDRAY wireless controller to meet network deployment requirements in environments including enterprises, schools, shopping malls, hotels, and financial organizations, etc.

➤ **All-round wireless security protection**

With the support of SUNDRAY wireless controller, AP-S150 provides a wide range of wireless security protection functions including WIDS/WIPS, illegitimate AP detection and workaround, ARP spoofing prevention, and DoS attack prevention, constructing a truly secure and reliable wireless network for users.

➤ **Timed turning off of RF for network security and environment protection**

RF can be turned off and on based on time periods. The wireless network can be automatically turned off at nights and weekends to prevent malicious users from intruding the network and to reduce energy consumption of the equipment.

## Flexible network deployment

- **Gateway function to implement remote deployment across the public network**

SUNDRAY AP-S150 supports the NAT gateway function and provides the functionality of the DHCP server and DNS proxy. When remotely deploying the wireless network for a branch or outlet, the PPPoE dial-up function provided by AP-S150 can be used to directly access the Internet, lowering the network construction costs.
- **Local forwarding**

With the local forwarding technology, AP-S150 can directly forward data that features high real-time transmission requirements, delay sensitivity, and large amount over the wired network without passing the wireless controller. This alleviates the traffic load of the wireless controller significantly and breaks the traffic restrictions of the wireless controller.
- **Virtual AP technology**

A maximum of 16 ESSIDs can be provided by using the virtual AP technology. Different SSIDs use different authentication modes and have different network access permission. The SSIDs are isolated from each other. L2 isolation can be implemented for terminals that use the same SSID on a subnet or VLAN to ensure user data security.
- **Chinese SSID**

Chinese SSIDs are supported. An SSID with a maximum of 32 characters can be specified. An SSID can also contain both Chinese and English characters. Individualized SSIDs are available for shopping malls or enterprises to improve discrimination.

## Marketing

- **Access analysis**

Build-in access analysis system, support report the device appear time, MAC address, and report the data differently in the first access and repeat access, passerby and total number coming and not coming in. Also will show the duration of stay. Based on the statistics, will have a better understanding of the clients in the network and offer information for the operators to make decision.
- **Marketing based on user behavior**

Based on the client's behavior to make the policy of when to push the message. The policy support based on the application the client is using, and based on location, schedule, first access repeat access. The message support banner, SMS, wechat message and webpage.
- **APP and file cache**

The controller can cache the application for ios and android devices. It will help to accelerate the network. Also it will help to accelerate the app authentication.

## Technical Specifications

### Hardware specifications

#### Product Specifications of SUNDRAY AP-S150

#### Hardware specifications

Item	Description
Model	AP S150
Weight	0.35kg
Dimensions (excluding antenna interfaces and accessories)	142 x 100 x 26 mm
Ethernet port	3*10/100 Mbps
Local power supply	DC 5V/1A
Transmit power	≤ 20 dBm
Power adjustment granularity	1 dBm
Power range	1 dBm to the value specified by national regulations
Power consumption	< 9W
Antenna	Embedded 2*2mimo antenna
Reset/restore factory settings	Supported
Status indicator	WLAN, 2*LAN, WAN, SYS, Power LED
Operating/storage temperature	-0°C ~ 40°C/-20°C ~ 70°C
Operating/storage humidity	10% ~ 90% / 5% ~ 95%
MTBF	> 250000 H

### Software specifications

Software specifications		
Item	Description	
Model	AP-S150	
RF	Streams	2
	Maximum transmission speed of a single frequency	300 Mbps
	Operating frequency band	802.11b/g/n: 2.4GHz-2.483GHz
	Modulation technology	OFDM : BPSK@6/9Mbps、QPSK@12/18Mbps、16-QAM@24Mbps、64-QAM@48/54Mbps
DSSS : DBPSK@1Mbps、DQPSK@2Mbps、CCK@5.5/11Mbps		
MIMO-OFDM : MCS 0-15		

Software specifications		
	Channel rate	802.11b: 1, 2, 5.5, 11 802.11g: 6, 9, 12, 18, 24, 36, 48, 54 802.11n: 6.5 to 300 (MCS0 to MCS15) 802.11n high throughput support: 20/40 11b: DSS:CCK@5.5/11Mbps,DQPSK@2Mbps,DBPSK@1Mbps 11g:OFDM:64QAM@48/54Mbps,16QAM@24Mbps,QPSK@12/18Mbps,BPSK@6/9Mbps 11n: MIMO-OFDM:BPSK,QPSK,16QAM,64QAM
	Channel quantity	802.11b、802.11g、802.11n: 13 channels
	Manual and automatic channel adjustment	Supported
	Automatic power adjustment	Supported
WLAN function	Manual power adjustment	The AP supports manual power adjustment with an adjustment granularity of 1 dBm. The power scope is from 1 dBm to the value specified by national regulations.
	Timed turning on or off of RF	RF can be turned on or off based on the specified time period.
	Coverage black hole detection and compensation	Supported
	Maximum number of connected users	128
	Connected user quantity restriction	Supported
	Virtual AP	16
	Chinese SSID	Supported
	SSID hiding	Supported
	Wireless relay/bridge	Point-to-point and point-to-multipoint supported
	User-, traffic-, and frequency band-based intelligent load balancing	Supported
Security authentication	Bandwidth restriction	STA-, SSID-, or AP-based rate limiting is supported.
	STA function	Abnormal STA disconnection detection, STA aging detection, and STA statistic and status query are supported.
	Link integrity detection	Supported
	Authentication mode	Pre-shared key authentication, portal authentication, 802.1x authentication, CA certificate authentication, WeChat authentication, SMS authentication, QR code authentication, temporary visitor authentication, and authentication exemption are supported.

Software specifications	
Pre-shared key	WPA-PSK, WPA2-PSK, WPA-PSK/WPA2-PSK hybrid authentication
Portal authentication	Intelligent terminal type identification is supported. A page matching the terminal size is pushed to terminals. The page logo and displayed information can be customized. In addition, the verification, authentication interval, and reconnection authentication time thresholds can be set.
802.1x authentication	802.1x one-key configuration and 802.1x perception-free authentication are supported. You only need to download the one-key automatic configuration tool at initial access and finish wireless network configuration quickly. This simplified network deployment significantly.
CA certificate authentication	High-security certificate authentication can be implemented by using the CA certificate issuance center embedded into the controller, without the need to constructing a certificate server. Authentication by using a certificate imported from an external certificate server is also supported.
WeChat authentication	After access the wireless network, a user can scan the QR code of the shopping mall or enterprise and follow the public account to access the Internet. The one-key follow function can be easily deployed without any code development. In WeChat authentication, a user can access the network by clicking a text message network access link or clicking the menu bar to view advertisements, or access the network via WeChat authorization.
Facebook	Support Facebook authentication, collecting user information like email, age, gender etc.
SMS authentication	SMS authentication takes effect forever. That is, a user can directly access the network without authentication after being authenticated via SMS at initial access. This reduces the SMS costs and improves user experience.
QR code authentication	After a visitor terminal accesses the wireless network, the terminal will automatically display a QR page. The approver scans the QR code of the visitor terminal via a cell phone and then the visitor can access the Internet. The visitor information is recorded in three dimensions: approver, remarks, and MAC address of the visitor terminal. This ensures user traceability and network security.

Software specifications		
	Temporary visitor authentication	A temporary user information management system is embedded. A temporary user can log in within the validity period and cannot after the validity period elapses. A secondary permission system for temporary account management is embedded and temporary accounts can be created and managed in this system. The QR code of a temporary visitor can be printed and the temporary visitor can scan the QR code to access the network. Temporary visitors can be grouped.
	Authentication exemption	Only a portal advertisement page is displayed. A user needs to click the login button to access the network without entering any account password or performing other authentication.
	Data encryption	Data encryption via TKIP and AES (CCMP) is supported.
	Blacklist and whitelist	Static whitelist and blacklist are supported.
	User isolation	SSID-based isolation, automatic VLAN grouping, and user isolation of specified VLANs are supported.
	WIPS	Supported
	Illegitimate AP detection and workaround	Supported
	ACL	Account-, access location-, access terminal type- and SSID-based ACL policy assignment and management are supported.
	Radius protocol	Supported
Wireless optimization	Application layer acceleration	Acceleration can be performed for the application layer. The acceleration service application can help increase the transmission speed by 1.5 to 4 times.
	E-schoolbag scenario optimization	The transmission speed of multicast packets is increased, improving the effects of the E-schoolbag scenario in an all-round way.
	Intelligent broadcast acceleration	The transmission speed of broadcast packets is automatically increased based on the actual environment, thereby improving the transmission efficiency of broadcast packets.
	Terminal dragging prevention	This function aims to prevent the decrease of the entire network speed caused by low-speed terminals based on the time fairness algorithm.
	Terminal viscosity prevention	This function involves detecting STAs connected to APs and intelligently guiding the STAs to the optimal AP.
	Prohibited access of low-speed terminals	The speed of access terminals is limited. Weak-signal terminals with a speed lower than the specified value are prohibited from accessing the network. This improves the entire network speed.
	High-density access scenario optimization	The response to broadcast probe requests is controlled for the purpose of optimizing high-density access scenarios.
	ARP-unicast conversion	ARP broadcast packets are converted into unicast packets. This reduces the number of broadcast packets, thereby improving the transmission speed.

Software specifications		
	Prohibited DHCP requests destined for wireless terminals	After this function is enabled, DHCP broadcast requests will be forwarded only to the wired network, instead of other wireless network. This improves the network throughput and performance of the wireless network.
Hotspot analysis	AP-based access user quantity statistics	The number of connected users and change trends of each AP in the recent one day, one week, and one month can be measured.
	AP-based network access traffic statistics	The network access traffic and change trends of each AP in the recent one day, one week, and one month can be measured.
	AP-based signal quality analysis	Statistic analysis for the signal usage, noise, retransmit rate, BER, and BER change trends of each AP is supported.
AP deployment	AC discovery mechanism	L2 broadcast automatic discovery L3 discovery based on configured static IP addresses DHCP Option43 discovery DNS domain name discovery
	Cross-WAN and cross-NAT remote AP deployment	Supported
	webAgent	Controller IP addresses can be dynamically discovered by using the webAgent technology. This avoids AP disconnection caused by unfixed controller IP addresses.
	Tunnel encryption	Supported
L3 function	NAT	Supported
	Network access mode	PPPoE dial-up and static IP address
	DHCP server	Supported
	DNS proxy	Supported

## Order Information

Model	Specifications	Remarks
<b>SUNDRAY AP S150 series</b>		
AP S150	AP S150 wireless access point is embedded with high gain antenna and supports 802.11a/b/g/n frequencies of 2.4 GHz.	Essential



**SANGFOR**  
深信服科技



**SUNDRAY**  
信锐技术

### Sundray Technologies Co., Ltd.

Add: Building A1, Nanshan iPark, No.1001 Xueyuan Road, Nanshan District, Shenzhen, Guangdong Province, P. R. China Post | Post Code: 518055

Service hot line: +86-755-86725911

[www.sangfor.com](http://www.sangfor.com)

[www.sundray.com](http://www.sundray.com)

E-mail: [liaohaibo@sundray.com](mailto:liaohaibo@sundray.com)

Copyright © 2015 Shenzhen Sundray Technologies Company Ltd. All rights reserved.

Disclaimer: Sundray Technologies retains the rights of final explanation and modification of this document and this statement.